

Instruments *(Continued)*

Example: When shift up rev setting is 10,000 r/min (rpm) and shift width setting is 200 r/min (rpm).

When the multi color line information is set to Rev up linkage mode (white color mode)

➡ **P.48** :

| multi color line | r/min (rpm) |
|------------------|-------------|
| Blinks | 9,600 |
| Blinks fast | 9,800 |
| Blinks faster | 10,000 |

When the multi color line information is set to Rev up linkage mode (color mode)

➡ **P.49** :

| multi color line | r/min (rpm) |
|------------------|-------------|
| Yellow | 9,600 |
| Amber | 9,800 |
| Pink | 10,000 |

If the shift width setting is 0 r/min (rpm), the multi color line starts to flash or lights in Pink (depends on Rev up linkage mode) when reaching to the setting value of shift up rev.

- 2 Press the **MODE** button. The shift width is set, and then the display moves to the time sign setting.